

## Q SERIES PETROL GENERATOR 3000W



|                           |                                     |
|---------------------------|-------------------------------------|
| <b>Model No:</b>          | FG4650Q                             |
| <b>EAN:</b>               | 0814726024833                       |
| <b>Continuous KW:</b>     | 2.80 kw                             |
| <b>Maximum KW:</b>        | 3.00 kw                             |
| <b>Noise Level at 7m:</b> | 71 dB(A)                            |
| <b>Warranty:</b>          | 3 Year Domestic / 1 Year Commercial |



### Description

The FG4650 Q Series Petrol Generator lives up to the Built Ford Tough standards. The single-cylinder 4-stroke OHV air-cooled engine provides a maximum output of 3.0kw and a continuous output of 2.8kw.

Dual voltage allows the generator to be used in either 110 volts or 230 volts. This allows the generator to be used for domestic use. Please Note: Dual voltage generators may only give approximately 50-60% of the rated output on 115V. Outputs are limited by the size of the sockets, based on the Voltage and Current (Power = Volts x Amps).

### Features

- Euro 5 Single cylinder 4-stroke OHV, air cooled engine
- Digital 3-in-1 meter (Voltage / Frequency / Time).
- Foldable handle for easy manoeuvrability.
- Circuit Protectors

### Specifications

|                              |                            |
|------------------------------|----------------------------|
| <b>Fuel Type:</b>            | Petrol                     |
| <b>Fuel Capacity:</b>        | 15 Litres                  |
| <b>Run Time At 50% Load:</b> | 15 Hours                   |
| <b>Starting Method:</b>      | Recoil                     |
| <b>Dimensions (WxHxL):</b>   | 570 x 550 x 610mm          |
| <b>Outlets:</b>              | 2 x 115V 16A, 1 x 230V 16A |
| <b>Engine Type:</b>          | 4-Stroke, Air Cooled, OHV  |
| <b>Engine Size:</b>          | 208cc                      |
| <b>Weight:</b>               | 45.00 kg                   |
| <b>Voltage:</b>              | 110 & 230V                 |
| <b>Frequency:</b>            | 50Hz                       |
| <b>AVR:</b>                  | Yes                        |
| <b>ATS:</b>                  | No                         |
| <b>Type:</b>                 | Petrol Generator           |