

## PETROL INVERTER GENERATOR 3800W



FG4500ISE
0814726027421
3.50 kw
3.80 kw
63 dB(A)
3 Year Domestic







## **Description**

The Ford FG4500iSE is the perfect generator to cover most domestic requirements along with providing power whilst camping or in a caravan away from a mains supplied site.

Boasting a large 3.8kW maximum output, the generator is ideal to take on sensitive work while allowing heavier equipment to be run off it simultaneously. Coupled with two 13 Amp, 230V domestic sockets, you can safely run multiple appliances without the worry of overloading and tripping out.

## **Features**

- ECO mode for lower fuel consumption and noise level.
- Sine wave output with a THD of <3%.
- Built in retractable handle and wheel kit for easy moving over flat ground.
- One push, electric start button.
- Low oil and overload warning light and automatic shutdown.
- 12V, 8A DC socket for battery charging.

## **Specifications**

Fuel Type:	Petrol
Fuel Capacity:	12 Litres
Run Time At 50% Load:	11 Hours
Starting Method:	Electric / Recoil
Dimensions (WxHxL):	470 x 530 x 640mm
Outlets:	2 x 230V 13A Outlet, 1 x 12V DC 8A, 1 x 5V DC 1.5A USB, Charging Facility
Engine Type:	Single Cylinder, 4-Stroke, Forced Air Cooling, OHV
Engine Size:	224cc
Weight:	47.00 kg
Voltage:	230V
Frequency:	50Hz
AVR:	No
ATS:	No
Pure Sine Wave:	Yes
Type:	Inverter Generator

